

Harmony - Power and Data Module

The new Harmony on desk module is the perfect solution for providing power and data sockets in offices and commercial spaces and has been designed to include a double end cap system that hides all visible fixing screws.



fig. 01

Main features

1. Choice of black, grey or white with matching inner and outer end caps as standard.
2. Available in five standard configurations but customised options are available on request.
3. Rear access Cat6, HDMI and USB data keystone. Cables are sold separately.
4. UK sockets feature integral fuses with a choice of 3.15A or 5A fuses to comply with BS 6396.
5. Tested to comply with BS 5733.
6. All standard options are supplied with a 1m mains lead to 3 pole connector. Starter leads with UK 13A plug are available on request.




fig. 02




fig. 03

Harmony - Power and Data Module

Harmony is available in three colours, black (fig. 04), grey (fig. 05) and white (fig. 06) with matching inner and outer end caps as standard but contrasting and coloured inner end caps are available subject to minimum order quantities and lead times.

Black/Silver



fig. 04

Grey/Silver



fig. 05

White/Silver



fig. 06

Dimensions and Fixing

The module dimensions are listed below for reference. To fix the module to the desk we recommending using our Harmony C clamp or adhesive fixing kit. Please note that two C clamps, for desks of 20-32mm thickness, should be used for module with more than 2 sockets. One adhesive fixing kit is required per module. Please see page 3 and 4.




fig. 07




fig. 08




fig. 09

Warning

Do not use this product for any purpose other than which it was designed for.

All electrical cables should be fitted by a qualified or competent person.

Do not dismantle or remodel the power module.

Cleaning, Storage & Maintenance

Cleaning & Maintenance	Dry cloth, no abrasives or solvents to be used on the module surface.
Handling & Storage	Do not drop or expose to moisture.

Harmony - Fixing Methods

C Clamp Fixing Kit Instructions

1. Apply rubber feet to the base of the Harmony module (fig. 10).
2. Place the unit in the desired position on the desk surface (fig. 11)
3. Fix the two C clamps at each end of the unit. Note, when a single C clamp is used you must ensure the C clamp is in the centre of the module (fig. 12).
4. Tighten the C clamp with a 5mm Allen key (not supplied). Do not use power tools.

fig. 10




fig. 11




fig. 12





fig. 13







Harmony - Fixing Methods

Adhesive Fixing Kit Instructions

1. Clean both mounting surfaces with the cleaning wipe provided.
2. Place the adhesive tabs (equally spaced) on the unit surface, ensuring the removal tab is partially exposed (fig. 14).
3. Position the unit on a clean, dry desk surface (fig. 15). Do not try to reposition after positioning.
4. Apply downward pressure for a minimum of 10 seconds. The product will be usable after 20 minutes.

Adhesive Fixing Kit Removal

1. Hold the unit firmly, whilst pulling the tab towards you (fig. 16).
2. Repeat this until all tabs have been removed (fig. 17).



Disclaimer: The adhesive strips have been rigorously tested to ensure that they function correctly on a wide range of surfaces. However we strongly recommend that you check with the supplier of the furniture prior to use. CMD Ltd will not be held liable for any subsequent damage that may occur during the normal use of this product. Failure to clean the surface will result in a poor bond, as will touching the cleaned areas.